chanhvinh.com

19-0411; Rev 4; 12/05

4-Pin µP Voltage Monitors with Manual Reset Input

General Description

The MAX811/MAX812 are low-power microprocessor (µP) supervisory circuits used to monitor power supplies in µP and digital systems. They provide excellent circuit reliability and low cost by eliminating external components and adjustments when used with 5V-powered or 3V-powered circuits. The MAX811/MAX812 also provide a debounced manual reset input.

These devices perform a single function: They assert a reset signal whenever the V_{CC} supply voltage falls below a preset threshold, keeping it asserted for at least 140ms after V_{CC} has risen above the reset threshold. The only difference between the two devices is that the MAX811 has an active-low RESET output (which is guaranteed to be in the correct state for V_{CC} down to 1V), while the MAX812 has an active-high RESET output. The reset comparator is designed to ignore fast transients on V_{CC}. Reset thresholds are available for operation with a variety of supply voltages.

Low supply current makes the MAX811/MAX812 ideal for use in portable equipment. The devices come in a 4-pin SOT143 package.

Applications

Computers

Controllers

Intelligent Instruments

Critical µP and µC Power Monitoring

Portable/Battery-Powered Equipment

Features

- **Precision Monitoring of 3V, 3.3V, and 5V Power-Supply Voltages**
- **6µA Supply Current**
- **140ms Min Power-On Reset Pulse Width; $\overline{\text{RESET}}$ Output (MAX811), RESET Output (MAX812)**
- **Guaranteed Over Temperature**
- **Guaranteed $\overline{\text{RESET}}$ Valid to V_{CC} = 1V (MAX811)**
- **Power-Supply Transient Immunity**
- **No External Components**
- **4-Pin SOT143 Package**

Ordering Information


PART*	TEMP RANGE	PIN-PACKAGE
MAX811_EUS-T	-40°C to +85°C	4 SOT143
MAX812_EUS-T	-40°C to +85°C	4 SOT143

**This part offers a choice of five different reset threshold voltages. Select the letter corresponding to the desired nominal reset threshold voltage, and insert it into the blank to complete the part number.*


Devices are available in both leaded and lead-free packaging. Specify lead-free by replacing "-T" with "+T" when ordering.

RESET THRESHOLD	
SUFFIX	VOLTAGE (V)
L	4.63
M	4.38
T	3.08
S	2.93
R	2.63

Typical Operating Circuit



Pin Configuration



For pricing, delivery, and ordering information, please contact Maxim/Dallas Direct! at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

chanhvinh.com

4-Pin µP Voltage Monitors with Manual Reset Input

ABSOLUTE MAXIMUM RATINGS

Terminal Voltage (with respect to GND)
- V_{CC} .....-0.3V to 6.0V
- All Other Inputs.....-0.3V to (V_{CC} + 0.3V)

Input Current, V_{CC}, $\overline{MR}$ 20mA
Output Current, RESET or $\overline{RESET}$ 20mA

Continuous Power Dissipation (T_A = +70°C)
SOT143 (derate 4mW/°C above +70°C) 320mW
Operating Temperature Range .....-40°C to +85°C
Storage Temperature Range .....-65°C to +160°C
Lead Temperature (soldering, 10sec) .....+300°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V_{CC} = 5V for L/M versions, V_{CC} = 3.3V for T/S versions, V_{CC} = 3V for R version, T_A = -40°C to +85°C, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Operating Voltage Range	V_{CC}	T_A = 0°C to +70°C		1.0		5.5	V
		T_A = -40°C to +85°C		1.2			
Supply Current	I_{CC}	MAX81_L/M, V_{CC} = 5.5V, I_{OUT} = 0			6	15	µA
		MAX81_R/S/T, V_{CC} = 3.6V, I_{OUT} = 0			2.7	10	
Reset Threshold	V_{TH}	MAX81_L	T_A = +25°C	4.54	4.63	4.72	V
			T_A = -40°C to +85°C	4.50		4.75	
		MAX81_M	T_A = +25°C	4.30	4.38	4.46	
			T_A = -40°C to +85°C	4.25		4.50	
		MAX81_T	T_A = +25°C	3.03	3.08	3.14	
			T_A = -40°C to +85°C	3.00		3.15	
		MAX81_S	T_A = +25°C	2.88	2.93	2.98	
			T_A = -40°C to +85°C	2.85		3.00	
		MAX81_R	T_A = +25°C	2.58	2.63	2.68	
			T_A = -40°C to +85°C	2.55		2.70	
Reset Threshold Tempco					30		ppm/°C
V_{CC} to Reset Delay (Note 2)		V_{OD} = 125mV, MAX81_L/M			40		µs
		V_{OD} = 125mV, MAX81_R/S/T			20		
Reset Active Timeout Period	t_{RP}	V_{CC} = $V_{TH(MAX)}$		140		560	ms
$\overline{MR}$ Minimum Pulse Width	t_{MR}			10			µs
$\overline{MR}$ Glitch Immunity (Note 3)					100		ns
$\overline{MR}$ to Reset Propagation Delay (Note 2)	t_{MD}				0.5		µs
$\overline{MR}$ Input Threshold	V_{IH}	V_{CC} > $V_{TH(MAX)}$, MAX81_L/M		2.3			V
	V_{IL}					0.8	
	V_{IH}	V_{CC} > $V_{TH(MAX)}$, MAX81_R/S/T		0.7 x V_{CC}			
	V_{IL}					0.25 x V_{CC}	
$\overline{MR}$ Pull-Up Resistance				10	20	30	kΩ
RESET Output Voltage (MAX812)	V_{OH}	I_{SOURCE} = 150µA, 1.8V < V_{CC} < $V_{TH(MIN)}$		0.8V_{CC}			V
	V_{OL}	MAX812R/S/T only, I_{SINK} = 1.2mA, V_{CC} = $V_{TH(MAX)}$				0.3	
		MAX812L/M only, I_{SINK} = 3.2mA, V_{CC} = $V_{TH(MAX)}$				0.4	

chanhvinh.com

ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = 5V for L/M versions, V_{CC} = 3.3V for T/S versions, V_{CC} = 3V for R version, T_A = -40°C to +85°C, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
$\overline{RESET}$ Output Voltage (MAX811)	V_{OL}	MAX811R/S/T only, I_{SINK} = 1.2mA, V_{CC} = $V_{TH(MIN)}$			0.3	V
		MAX811L/M only, I_{SINK} = 3.2mA, V_{CC} = $V_{TH(MIN)}$			0.4	
		I_{SINK} = 50µA, V_{CC} > 1.0V			0.3	
	V_{OH}	MAX811R/S/T only, I_{SOURCE} = 500µA, V_{CC} > $V_{TH(MAX)}$	0.8V_{CC}			
		MAX811L/M only, I_{SOURCE} = 800µA, V_{CC} > $V_{TH(MAX)}$	V_{CC} - 1.5			

Note 1: Production testing done at T_A = +25°C, over temperature limits guaranteed by design using six sigma design limits.
Note 2: $\overline{RESET}$ output for MAX811, RESET output for MAX812.
Note 3: "Glitches" of 100ns or less typically will not generate a reset pulse.


chanhvinh.com

4-Pin µP Voltage Monitors with Manual Reset Input


Typical Operating Characteristics

(T_A = +25°C, unless otherwise noted.)


SUPPLY CURRENT vs. TEMPERATURE (MAX81_R/S/T)




SUPPLY CURRENT vs. TEMPERATURE (MAX81_L/M)




POWER-DOWN RESET DELAY vs. TEMPERATURE (MAX81_R/S/T)




POWER-DOWN RESET DELAY vs. TEMPERATURE (MAX81_L/M)



POWER-UP RESET TIMEOUT vs. TEMPERATURE



RESET THRESHOLD DEVIATION vs. TEMPERATURE



chanhvinh.com

4-Pin µP Voltage Monitors with Manual Reset Input

Pin Description

PIN		NAME	FUNCTION
MAX811	MAX812		
1	1	GND	Ground
2	—	$\overline{\text{RESET}}$	Active-Low Reset Output. $\overline{\text{RESET}}$ remains low while V_{CC} is below the reset threshold or while $\overline{\text{MR}}$ is held low. $\overline{\text{RESET}}$ remains low for the Reset Active Timeout Period (t_{RP}) after the reset conditions are terminated.
—	2	RESET	Active-High Reset Output. RESET remains high while V_{CC} is below the reset threshold or while $\overline{\text{MR}}$ is held low. RESET remains high for Reset Active Timeout Period (t_{RP}) after the reset conditions are terminated.
3	3	$\overline{\text{MR}}$	Manual Reset Input. A logic low on $\overline{\text{MR}}$ asserts reset. Reset remains asserted as long as $\overline{\text{MR}}$ is low and for 180ms after $\overline{\text{MR}}$ returns high. This active-low input has an internal 20kΩ pull-up resistor. It can be driven from a TTL or CMOS-logic line, or shorted to ground with a switch. Leave open if unused.
4	4	V_{CC}	+5V, +3.3V, or +3V Supply Voltage

Detailed Description

Reset Output

A microprocessor's (µP's) reset input starts the µP in a known state. These µP supervisory circuits assert reset to prevent code execution errors during power-up, power-down, or brownout conditions.

$\overline{\text{RESET}}$ is guaranteed to be a logic low for V_{CC} > 1V. Once V_{CC} exceeds the reset threshold, an internal timer keeps $\overline{\text{RESET}}$ low for the reset timeout period; after this interval, $\overline{\text{RESET}}$ goes high.

If a brownout condition occurs (V_{CC} dips below the reset threshold), $\overline{\text{RESET}}$ goes low. Any time V_{CC} goes below the reset threshold, the internal timer resets to zero, and $\overline{\text{RESET}}$ goes low. The internal timer starts after V_{CC} returns above the reset threshold, and $\overline{\text{RESET}}$ remains low for the reset timeout period.

The manual reset input ($\overline{\text{MR}}$) can also initiate a reset. See the *Manual Reset Input* section.

The MAX812 has an active-high RESET output that is the inverse of the MAX811's $\overline{\text{RESET}}$ output.

Manual Reset Input

Many µP-based products require manual reset capability, allowing the operator, a test technician, or external logic circuitry to initiate a reset. A logic low on $\overline{\text{MR}}$ asserts reset. Reset remains asserted while $\overline{\text{MR}}$ is low, and for the Reset Active Timeout Period (t_{RP}) after $\overline{\text{MR}}$ returns high. This input has an internal 20kΩ pull-up resistor, so it can be left open if it is not used. $\overline{\text{MR}}$ can be driven with TTL or CMOS-logic levels, or with open-drain/collector outputs. Connect a normally open momentary switch from $\overline{\text{MR}}$ to GND to create a manual-reset function; external debounce circuitry is not required. If $\overline{\text{MR}}$ is driven from long cables or if the device is used in a noisy environment, connecting a 0.1µF capacitor from $\overline{\text{MR}}$ to ground provides additional noise immunity.

Reset Threshold Accuracy

The MAX811/MAX812 are ideal for systems using a 5V ±5% or 3V ±5% power supply with ICs specified for 5V ±10% or 3V ±10%, respectively. They are designed to meet worst-case specifications over temperature. The reset is guaranteed to assert after the power supply falls out of regulation, but before power drops below the minimum specified operating voltage range for the system ICs. The thresholds are pre-trimmed and exhibit tight distribution, reducing the range over which an undesirable reset may occur.

chanhvinh.com

4-Pin µP Voltage Monitors with Manual Reset Input




Figure 1. Maximum Transient Duration without Causing a Reset Pulse vs. Comparator Overdrive




Figure 2. RESET Valid to VCC = Ground Circuit

Applications Information

Negative-Going VCC Transients

In addition to issuing a reset to the µP during power-up, power-down, and brownout conditions, the MAX811/MAX812 are relatively immune to short duration negative-going VCC transients (glitches).

Figure 1 shows typical transient durations vs. reset comparator overdrive, for which the MAX811/MAX812 do not generate a reset pulse. This graph was generated using a negative-going pulse applied to VCC, starting above the actual reset threshold and ending below it by the magnitude indicated (reset comparator overdrive). The graph indicates the typical maximum pulse width a negative-going VCC transient may have without causing a reset pulse to be issued. As the magnitude of the transient increases (goes farther below the reset threshold), the maximum allowable pulse width decreases. Typically, a VCC transient that goes 125mV below the reset threshold and lasts 40µs or less (MAX81_L/M) or 20µs or less (MAX81_T/S/R) will not cause a reset pulse to be issued. A 0.1µF capacitor mounted as close as possible to VCC provides additional transient immunity.

Ensuring a Valid RESET Output Down to VCC = 0V

When VCC falls below 1V, the MAX811 $\overline{\text{RESET}}$ output no longer sinks current—it becomes an open circuit. Therefore, high-impedance CMOS-logic inputs connected to the $\overline{\text{RESET}}$ output can drift to undetermined voltages. This presents no problem in most applications, since most µP and other circuitry is inoperative with VCC below 1V. However, in applications where the $\overline{\text{RESET}}$ output must be valid down to 0V, adding a pull-down resistor to the $\overline{\text{RESET}}$ pin will cause any stray leakage currents to flow to ground, holding $\overline{\text{RESET}}$ low (Figure 2). R1's value is not critical; 100kΩ is large enough not to load $\overline{\text{RESET}}$ and small enough to pull $\overline{\text{RESET}}$ to ground.

A 100kΩ pull-up resistor to VCC is also recommended for the MAX812 if RESET is required to remain valid for VCC < 1V.

chanhvinh.com

Interfacing to µPs with Bidirectional Reset Pins

µPs with bidirectional reset pins (such as the Motorola 68HC11 series) can contend with the MAX811/MAX812 reset outputs. If, for example, the MAX811 $\overline{\text{RESET}}$ output is asserted high and the µP wants to pull it low, indeterminate logic levels may result. To correct such cases, connect a 4.7kΩ resistor between the MAX811 $\overline{\text{RESET}}$ (or MAX812 RESET) output and the µP reset I/O (Figure 3). Buffer the reset output to other system components.




Figure 3. Interfacing to µPs with Bidirectional Reset I/O

Chip Information


TRANSISTOR COUNT: 341

chanhvinh.com

4-Pin µP Voltage Monitors with Manual Reset Input

Package Information

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to **www.maxim-ic.com/packages**.)




NOTE: DIMENSIONS ARE IN MM.
AND FOLLOW EIA481-1 STANDARD.

MARKING INFORMATION†

XX XX
- LOT SPECIFIC CODE

AMAA or KABB = MAX811L
ANAA or KABC = MAX811M
APAA or KABD = MAX811T
AQAA or KABE = MAX811S
ARAA or KABF = MAX811R
ASAA or KABG = MAX812L
ATAA or KABH = MAX812M
AVAA or KABI = MAX812T
AWAA or KABJ = MAX812S
AXAA or KABK = MAX812R

† ICs MAY ALSO BE MARKED WITH FULL PART NAME: 811L, 811M_...



DIM	INCHES MIN	INCHES MAX	MILLIMETERS MIN	MILLIMETERS MAX
A	0.031	0.048	0.80	1.22
A1	0.000	0.006	0.01	0.15
b	0.014	0.020	0.35	0.50
b1	0.012	0.018	0.30	0.45
b2	0.030	0.035	0.76	0.89
b3	0.012	0.033	0.76	0.84
c	0.003	0.008	0.08	0.20
c1	0.003	0.006	0.08	0.16
D	0.110	0.120	2.80	3.04
E	0.083	0.104	2.10	2.64
E1	0.047	0.055	1.20	1.40
e	0.076 BSC.		1.92 BSC.	
e1	0.008 BSC.		0.20 BSC.	
L	0.016	0.024	0.40	0.60
L1	0.021 REF.		0.54 REF.	
S	0.018	0.024	0.45	0.60
α	0°	8°	0°	8°

SOT-143 4LEPS

NOTES:
1. D&E DO NOT INCLUDE MOLD FLASH.
2. MOLD FLASH OR PROTRUSIONS NOT TO EXCEED .15mm (.006").
3. CONTROLLING DIMENSION: MILLIMETERS.
4. MEETS JEDEC TO253.
5. THESE DIMENSIONS APPLY TO THE FLAT SECTION OF THE LEAD BETWEEN 0.08mm AND 0.15mm FROM THE LEAD TIP.

DALLAS SEMICONDUCTOR MAXIM
PROPRIETARY INFORMATION
TITLE: PACKAGE OUTLINE, SOT-143, 4L
APPROVAL | DOCUMENT CONTROL NO. 21-0052 | REV. E | 1/1

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 2005 Maxim Integrated Products Printed USA MAXIM is a registered trademark of Maxim Integrated Products, Inc.