chanhvinh.com

Data Sheet No. PD60249

International
IOR Rectifier

IRS2110(-1,-2,S)PbF
IRS2113(-1,-2,S)PbF

HIGH AND LOW SIDE DRIVER

Features

- Floating channel designed for bootstrap operation
- Fully operational to +500 V or +600 V
- Tolerant to negative transient voltage, dV/dt immune
- Gate drive supply range from 10 V to 20 V
- Undervoltage lockout for both channels
- 3.3 V logic compatible
- Separate logic supply range from 3.3 V to 20 V
- Logic and power ground ± 5V offset
- CMOS Schmitt-triggered inputs with pull-down
- Cycle by cycle edge-triggered shutdown logic
- Matched propagation delay for both channels
- Outputs in phase with inputs
- RoHS compliant

Description

The IRS2110/IRS2113 are high voltage, high speed power MOSFET and IGBT drivers with independent high-side and low-side referenced output channels. Proprietary HVIC and latch immune CMOS technologies enable ruggedized monolithic construction. Logic inputs are compatible with standard CMOS or LSTTL output, down to 3.3 V logic. The output drivers feature a high pulse current buffer stage designed for minimum driver cross-conduction. Propagation delays are matched to simplify use in high frequency applications. The floating channel can be used to drive an N-channel power MOSFET or IGBT in the high-side configuration which operates up to 500 V or 600 V.

Product Summary

V_{OFFSET} (IRS2110) (IRS2113)	500 V max. 600 V max.
I_O+/-	2 A/2 A
V_{OUT}	10 V - 20 V
$t_{on/off}$ (typ.)	130 ns & 120 ns
Delay Matching (IRS2110) (IRS2113)	10 ns max. 20 ns max.

Packages



14-Lead PDIP
IRS2110 and IRS2113



16-Lead PDIP
(w/o leads 4 & 5)
IRS2110-2 and IRS2113-2



14-Lead PDIP
(w/o lead 4)
IRS2110-1 and IRS2113-1



16-Lead SOIC
IRS2110S and
IRS2113S

Typical Connection



(Refer to Lead Assignments for correct pin configuration). This diagram shows electrical connections only. Please refer to our Application Notes and DesignTips for proper circuit board layout.

chanhvinh.com

Absolute Maximum Ratings

Absolute maximum ratings indicate sustained limits beyond which damage to the device may occur. All voltage parameters are absolute voltages referenced to COM. The thermal resistance and power dissipation ratings are measured under board mounted and still air conditions. Additional information is shown in Figs. 28 through 35.

Symbol	Definition		Min.	Max.	Units
V_B	High-side floating supply voltage	(IRS2110)	-0.3	520 (Note 1)	V
		(IRS2113)	-0.3	620 (Note 1)	
V_S	High-side floating supply offset voltage		V_B - 20	V_B + 0.3	
V_{HO}	High-side floating output voltage		V_S - 0.3	V_B + 0.3	
V_{CC}	Low-side fixed supply voltage		-0.3	20 (Note 1)	
V_{LO}	Low-side output voltage		-0.3	V_{CC} + 0.3	
V_{DD}	Logic supply voltage		-0.3	V_{SS}+20 (Note 1)	
V_{SS}	Logic supply offset voltage		V_{CC} - 20	V_{CC} + 0.3	
V_{IN}	Logic input voltage (HIN, LIN, & SD)		V_{SS} - 0.3	V_{DD} + 0.3	
dV_S/dt	Allowable offset supply voltage transient (Fig. 2)		—	50	V/ns
P_D	Package power dissipation @ $T_A \leq +25$ °C	(14 lead DIP)	—	1.6	W
		(16 lead SOIC)	—	1.25	
R_{THJA}	Thermal resistance, junction to ambient	(14 lead DIP)	—	75	°C/W
		(16 lead SOIC)	—	100	
T_J	Junction temperature		—	150	°C
T_S	Storage temperature		-55	150	
T_L	Lead temperature (soldering, 10 seconds)		—	300	

Note 1: All supplies are fully tested at 25 V, and an internal 20 V clamp exists for each supply.

Recommended Operating Conditions

The input/output logic timing diagram is shown in Fig. 1. For proper operation, the device should be used within the recommended conditions. The V_S and V_{SS} offset ratings are tested with all supplies biased at a 15 V differential. Typical ratings at other bias conditions are shown in Figs. 36 and 37.

Symbol	Definition		Min.	Max.	Units
V_B	High-side floating supply absolute voltage		V_S + 10	V_S + 20	V
VS	High-side floating supply offset voltage	(IRS2110)	Note 2	500	
		(IRS2113)	Note 2	600	
V_{HO}	High-side floating output voltage		V_S	V_B	
V_{CC}	Low-side fixed supply voltage		10	20	
V_{LO}	Low-side output voltage		0	VCC	
V_{DD}	Logic supply voltage		V_{SS} + 3	V_{SS} + 20	
V_{SS}	Logic supply offset voltage		-5 (Note 3)	5	
V_{IN}	Logic input voltage (HIN, LIN & SD)		V_{SS}	V_{DD}	
T_A	Ambient temperature		-40	125	°C

Note 2: Logic operational for V_S of -4 V to +500 V. Logic state held for V_S of -4 V to $-V_{BS}$. (Refer to the Design Tip DT97-3)
Note 3: When $V_{DD} < 5$ V, the minimum V_{SS} offset is limited to $-V_{DD}$.

chanhvinh.com

Dynamic Electrical Characteristics

V_{BIAS} (V_{CC}, V_{BS}, V_{DD}) = 15 V, C_L = 1000 pF, T_A = 25 °C and V_{SS} = COM unless otherwise specified. The dynamic electrical characteristics are measured using the test circuit shown in Fig. 3.

Symbol	Definition		Min.	Typ.	Max.	Units	Test Conditions
t_{on}	Turn-on propagation delay		—	130	160	ns	V_S = 0 V
t_{off}	Turn-off propagation delay		—	120	150		V_S = 500 V/600 V
t_{sd}	Shutdown propagation delay		—	130	160		
t_r	Turn-on rise time		—	25	35		
t_f	Turn-off fall time		—	17	25		
MT	Delay matching, HS & LS turn-on/off	(IRS2110)	—	—	10		
		(IRS2113)	—	—	20		

Static Electrical Characteristics

V_{BIAS} (V_{CC}, V_{BS}, V_{DD}) = 15 V, T_A = 25 °C and V_{SS} = COM unless otherwise specified. The V_{IN}, V_{TH}, and I_{IN} parameters are referenced to V_{SS} and are applicable to all three logic input leads: HIN, LIN, and SD. The V_O and I_O parameters are referenced to COM and are applicable to the respective output leads: HO or LO.

Symbol	Definition	Min.	Typ.	Max.	Units	Test Conditions
V_{IH}	Logic “1” input voltage	9.5	—	—	V	
V_{IL}	Logic “0” input voltage	—	—	6.0		
V_{OH}	High level output voltage, V_{BIAS} - V_O	—	—	1.4		I_O = 0 A
V_{OL}	Low level output voltage, V_O	—	—	0.15		I_O = 20 mA
I_{LK}	Offset supply leakage current	—	—	50	µA	V_B=V_S = 500 V/600 V
I_{QBS}	Quiescent V_{BS} supply current	—	125	230		V_{IN} = 0 V or V_{DD}
I_{QCC}	Quiescent V_{CC} supply current	—	180	340		
I_{QDD}	Quiescent V_{DD} supply current	—	15	30		
I_{IN+}	Logic “1” input bias current	—	20	40		V_{IN} = V_{DD}
I_{IN-}	Logic “0” input bias current	—	—	5.0		V_{IN} = 0 V
V_{BSUV+}	V_{BS} supply undervoltage positive going threshold	7.5	8.6	9.7	V	
V_{BSUV-}	V_{BS} supply undervoltage negative going threshold	7.0	8.2	9.4		
V_{CCUV+}	V_{CC} supply undervoltage positive going threshold	7.4	8.5	9.6		
V_{CCUV-}	V_{CC} supply undervoltage negative going threshold	7.0	8.2	9.4		
I_{O+}	Output high short circuit pulsed current	2.0	2.5	—	A	V_O = 0 V, V_{IN} = V_{DD} PW ≤ 10 µs
I_{O-}	Output low short circuit pulsed current	2.0	2.5	—		V_O = 15 V, V_{IN} = 0V PW ≤ 10 µs

chanhvinh.com

Functional Block Diagram



Lead Definitions

Symbol	Description
V_{DD}	Logic supply
HIN	Logic input for high-side gate driver output (HO), in phase
SD	Logic input for shutdown
LIN	Logic input for low-side gate driver output (LO), in phase
V_{SS}	Logic ground
V_B	High-side floating supply
HO	High-side gate drive output
V_S	High-side floating supply return
V_{CC}	Low-side supply
LO	Low-side gate drive output
COM	Low-side return

chanhvinh.com

Lead Assignments

 14 Lead PDIP **IRS2110/IRS2113**	 16 Lead SOIC (Wide Body) **IRS2110S/IRS2113S**
 14 Lead PDIP w/o lead 4 **IRS2110-1/IRS2113-1**	 16 Lead PDIP w/o leads 4 & 5 **IRS2110-2/IRS2113-2**
Part Number	

chanhvinh.com



Figure 1. Input/Output Timing Diagram



Figure 2. Floating Supply Voltage Transient Test Circuit



Figure 3. Switching Time Test Circuit



Figure 4. Switching Time Waveform Definition



Figure 5. Shutdown Waveform Definitions



Figure 6. Delay Matching Waveform Definitions

chanhvinh.com



Figure 7A. Turn-On Time vs. Temperature



Figure 7B. Turn-On Time vs. Supply Voltage



Figure 7C. Turn-On Time vs. V_{DD} Supply Voltage



Figure 8A. Turn-Off Time vs. Temperature



Figure 8B. Turn-Off Time vs. Supply Voltage



Figure 8C. Turn-Off Time vs. V_{DD} Supply Voltage

chanhvinh.com



Figure 9A. Shutdown Time vs. Temperature



Figure 9B. Shutdown Time vs. Supply Voltage



Figure 9C. Shutdown Time vs. V_{DD} Supply Voltage



Figure 10A. Turn-On Rise Time vs. Temperature



Figure 10B. Turn-On Rise Time vs. Voltage



Figure 11A. Turn-Off Fall Time vs. Temperature

chanhvinh.com



Figure 11B. Turn-Off Fall Time vs. Voltage



Figure 12A. Logic "1" Input Threshold vs. Temperature



Figure 12B. Logic "1" Input Threshold vs. Voltage



Figure 13A. Logic "0" Input Threshold vs. Temperature



Figure 13B. Logic "0" Input Threshold vs. Voltage



Figure 14A. High Level Output Voltage vs. Temperature (I_O = 0 mA)

chanhvinh.com



Figure 14B. High Level Output Voltage vs. Supply Voltage (I_O = 0 mA)



Figure 15A. Low Level Output vs. Temperature



Figure 15B. Low Level Output vs. Supply Voltage



Figure 16A. Offset Supply Current vs. Temperature



Figure 16B. Offset Supply Current vs. Voltage



Figure 17A. V_{BS} Supply Current vs. Temperature

chanhvinh.com



Figure 17B. V_{BS} Supply Current vs. Voltage



Figure 18A. V_{CC} Supply Current vs. Temperature



Figure 18B. V_{CC} Supply Current vs. Voltage



Figure 19A. V_{DD} Supply Current vs. Temperature



Figure 19B. V_{DD} Supply Current vs. V_{DD} Voltage



Figure 20A. Logic "1" Input Current vs. Temperature

chanhvinh.com



Figure 20B. Logic "1" Input Current vs. V_{DD} Voltage



Figure 21A. Logic "0" Input Bias Current vs. Temperature



Figure 21B. Logic "0" Input Bias Current vs. Voltage



Figure 22. V_{BS} Undervoltage (+) vs. Temperature



Figure 23. V_{BS} Undervoltage (-) vs. Temperature



Figure 24. V_{CC} Undervoltage (+) vs. Temperature

chanhvinh.com



Figure 25. V_{CC} Undervoltage (-) vs. Temperature



Figure 26A. Output Source Current vs. Temperature



Figure 26B. Output Source Current vs. Voltage



Figure 27A. Output Sink Current vs. Temperature



Figure 27B. Output Sink Current vs. Voltage



Figure 28. IRS2110/IRS2113 T_J vs. Frequency (IRFBC20) R_{GATE} = 33 Ω, V_{CC} = 15 V

chanhvinh.com



Figure 29. IRS2110/IRS2113 T_J vs. Frequency (IRFBC30) R_{GATE} = 22 Ω, V_{CC} = 15 V



Figure 30. IRS2110/IRS2113 T_J vs. Frequency (IRFBC40) R_{GATE} = 15 Ω, V_{CC} = 15 V



Figure 31. IRS2110/IRS2113 T_J vs. Frequency (IRFPE50) R_{GATE} = 10 Ω, V_{CC} = 15 V



Figure 32. IRS2110S/IRS2113S T_J vs. Frequency (IRFBC20) R_{GATE} = 33 Ω, V_{CC} = 15 V



Figure 33. IRS2110S/IRS2113S T_J vs. Frequency (IRFBC30) R_{GATE} = 22 Ω, V_{CC} = 15 V



Figure 34. IRS2110S/IRS2113S T_J vs. Frequency (IRFBC40) R_{GATE} = 15 Ω, V_{CC} = 15 V

chanhvinh.com



Figure 35. IRS2110S/IRS2113S T_J vs. Frequency (IRFPE50) R_{GATE} = 10 Ω, V_{CC} = 15 V



Figure 36. Maximum V_S Negative Offset vs. V_{BS} Supply Voltage



Figure 37. Maximum V_{SS} Positive Offset vs. V_{CC} Supply Voltage

chanhvinh.com

Case Outlines



14-Lead PDIP 01-6010
01-3002 03 (MS-001AC)



14-Lead PDIP w/o Lead 4 01-6010
01-3008 02 (MS-001AC)

chanhvinh.com



16 Lead PDIP w/o Leads 4 & 5

01-6015
01-3010 02



16-Lead SOIC (wide body)

01 6015
01-3014 03 (MS-013AA)

chanhvinh.com

Tape & Reel
16-Lead SOIC



CARRIER TAPE DIMENSION FOR 16SOICW

Code	Metric		Imperial	
	Min	Max	Min	Max
A	11.90	12.10	0.468	0.476
B	3.90	4.10	0.153	0.161
C	15.70	16.30	0.618	0.641
D	7.40	7.60	0.291	0.299
E	10.80	11.00	0.425	0.433
F	10.60	10.80	0.417	0.425
G	1.50	n/a	0.059	n/a
H	1.50	1.60	0.059	0.062



REEL DIMENSIONS FOR 16SOICW

Code	Metric		Imperial	
	Min	Max	Min	Max
A	329.60	330.25	12.976	13.001
B	20.95	21.45	0.824	0.844
C	12.80	13.20	0.503	0.519
D	1.95	2.45	0.767	0.096
E	98.00	102.00	3.858	4.015
F	n/a	22.40	n/a	0.881
G	18.50	21.10	0.728	0.830
H	16.40	18.40	0.645	0.724

chanhvinh.com

LEADFREE PART MARKING INFORMATION



?	MARKING CODE
P	Lead Free Released
	Non-Lead Free Released

ORDER INFORMATION

14-Lead PDIP IRS2110PbF
14-Lead PDIP IRS2110-1PbF
14-Lead PDIP IRS2113PbF
14-Lead PDIP IRS2113-1PbF
16-Lead PDIP IRS2110-2PbF
16-Lead PDIP IRS2113-2PbF
16-Lead SOIC IRS2110SPbF
16-Lead SOIC IRS2113SPbF
16-Lead SOIC Tape & Reel IRS2110STRPbF
16-Lead SOIC Tape & Reel IRS2113STRPbF

The SOIC-14 is MSL3 qualified.
The SOIC-16 is MSL3 qualified.
This product has been designed and qualified for the industrial level.
Qualification standards can be found at www.irf.com

IR WORLD HEADQUARTERS: 233 Kansas St., El Segundo, California 90245 Tel: (310) 252-7105

Data and specifications subject to change without notice. 1/22/2007