chanhvinh.com

Up/Down Counting Pulse Indicator
K3HB-C

CSM_K3HB-C_DS_E_15_1

Measure High-speed Up/down Pulses with this Up/down Pulse Meter.

- Visual conf0rmation of judgement results through display colors that switch between red and green. ✻1
- Perfect for Measuring Rotary Encoder and ON/OFF Pulse Signals at High Speed
  Cumulative pulse input is 50 kHz, quadrature pulse inputs are 25 kHz, and up/down pulse inputs are 30 kHz.

Note: No-voltage contacts of up to 30 Hz are supported.

- The count value can be converted to any value.
  The length equivalent for any pulse can be set to any desired value. This is effective for feed amount and position monitor displays.
- DeviceNet models added to the series. ✻2

✻1 Visual confirmation of judgement results is not supported on models that do not have an output or models that do not support DeviceNet.
You can change the display color by setting it, but you cannot switch it based on the judgement results.

✻2 DeviceNet models have a depth of 97 mm.

⚠ Refer to *Safety Precautions for All Digital Panel Meters*.



For the most recent information on models that have been certified for safety standards, refer to your OMRON website.

Model Number Structure

■ Model Number Legend

Base Units and Optional Boards can be ordered individually or as sets.

Base Units

K3HB-C □ □
1 5

1. **Input Sensor Code**
   NB: NPN input/voltage pulse input
5. **Supply Voltage**
   100-240 VAC: 100 to 240 VAC
   24 VAC/VDC: 24 VAC/VDC

Optional Board

Sensor Power Supply/Output Boards

K33-□
2

Relay/Transistor Output Boards

K34-□
3

Event Input Boards

K35-□
4

Base Units with Optional Boards

K3HB-C□**-**□□□ □
1 2 3 4 5

2. **Sensor Power Supply/Output Type Code**
   None: None
   CPA: Relay output (PASS: SPDT) + Sensor power supply (12 VDC±10%, 80 mA) (See note 1.)
   L1A: Linear current output (0 to 20 or 4 to 20 mA DC) + Sensor power supply (12 VDC±10%, 80 mA) (See note 2.)
   L2A: Linear voltage output (0 to 5, 1 to 5, or 0 to 10 VDC) + Sensor power supply (12 VDC±10%, 80 mA) (See note 2.)
   A: Sensor power supply (12 VDC ±10%, 80 mA)
   FLK1A: Communications (RS-232C) + Sensor power supply (12 VDC±10%, 80 mA) (See note 2.)
   FLK3A: Communications (RS-485) + Sensor power supply (12 VDC±10%, 80 mA) (See note 2.)

Note: 1. CPA can be combined with relay outputs only.
2. Only one of the following can be used by each Digital Indicator: RS-232C/RS-485 communications, a linear output, or DeviceNet communications.

3. **Relay/Transistor Output Type Code**
   None: None
   C2: Relay contact (HH/H/LL/L: SPST-NO each)
   T1: Transistor (NPN open collector: HH/H/PASS/L/LL)
   T2: Transistor (PNP open collector: HH/H/PASS/L/LL)
   BCD✻: BCD output + transistor output (NPN open collector: HH/H/PASS/L/LL)
   DRT: DeviceNet (See note 2.)
   ✻ A Special BCD Output Cable (sold separately) is required.
4. **Event Input Type Code**
   None: None
   1: 5 inputs (M3 terminal block), NPN open collector
   2: 8 inputs (10-pin MIL connector), NPN open collector
   3: 5 inputs (M3 terminal block), PNP open collector
   4: 8 inputs (10-pin MIL connector), PNP open collector

Note: The following combinations are not possible.
- Communications (FLK□A) + DeviceNet (DRT)
- Communications (FLK□A) + BCD output (BCD)
- Linear current/voltage (L□A) + DeviceNet (DRT)

chanhvinh.com

Accessories (Sold Separately)

K32-DICN: Special Cable (for event inputs with 8-pin connector)

K32-BCD: Special BCD Output Cable

Watertight Cover

Model
Y92A-49N

Rubber Packing

Model
K32-P1

Note: Rubber packing is provided with the Controller.

Specifications

■ Ratings

Supply voltage		100 to 240 VAC, 24 VAC/VDC, DeviceNet power supply: 24 VDC
Allowable power supply voltage range		85% to 110% of the rated power supply voltage, DeviceNet power supply: 11 to 25 VDC
Power consumption (See note 1.)		100 to 240 VAC: 18 VA max. (max. load) 24 VAC/DC: 11 VA/7 W max. (max. load)
Current consumption		DeviceNet power supply: 50 mA max. (24 VDC)
Input		No-voltage contact, voltage pulse, open collector
External power supply		12 VDC±10% 80 mA
Event inputs	**Hold input**	NPN open collector or no-voltage contact signal ON residual voltage: 2 V max. ON current at 0 Ω: 4 mA max. Max. applied voltage: 30 VDC max. OFF leakage current: 0.1 mA max.
	Reset input	
	Bank input	
Output ratings (depends on the model)	**Relay output**	250 VAC, 30 VDC, 5 A (resistive load) Mechanical life expectancy: 5,000,000 operations, Electrical life expectancy: 100,000 operations
	Transistor output	Maximum load voltage: 24 VDC, Maximum load current: 50 mA, Leakage current: 100 μA max.
	Linear output	Linear output 0 to 20 mA DC, 4 to 20 mA DC: Load: 500 Ω max, Resolution: Approx. 10,000, Output error: ±0.5% FS Linear output 0 to 5 VDC, 1 to 5 VDC, 0 to 10 VDC: Load: 5 kΩ max, Resolution: Approx. 10,000, Output error: ±0.5% FS (1 V or less: ±0.15 V; no output for 0 V or less)
Display method		Negative LCD (backlit LED) display 7-segment digital display (Character height: PV: 14.2 mm (green/red); SV: 4.9 mm (green))
Main functions		Scaling function, measurement operation selection, output hysteresis, output OFF delay, output test, display value selection, display color selection, key protection, bank selection, display refresh period, maximum/minimum hold, reset
Ambient operating temperature		–10 to 55°C (with no icing or condensation)
Ambient operating humidity		25% to 85%
Storage temperature		–25 to 65°C (with no icing or condensation)
Altitude		2,000 m max.
Accessories		Watertight packing, 2 fixtures, terminal cover, unit stickers, instruction manual. DeviceNet models also include a DeviceNet connector (Hirose HR31-5.08P-5SC(01)) and crimp terminals (Hirose HR31-SC-121) (See note 3.)

Note: 1. DC power supply models require a control power supply capacity of approximately 1 A per Unit when power is turned ON. Particular attention is required when using two or more DC power supply models. The OMRON S8VS-series DC Power Supply Unit is recommended.

2. For K3HB-series DeviceNet models, use only the DeviceNet Connector included with the product. The crimp terminals provided are for Thin Cables.

chanhvinh.com

■ Characteristics

<table>
<tr><td colspan="2">Display range</td><td>–19,999 to 99,999</td></tr>
<tr><td colspan="2">Measurement range</td><td>Functions F1, F2: ±2 gigacounts
Functions F3: 0 to 4 gigacounts</td></tr>
<tr><td colspan="2">Input signals</td><td>• Contact input (dry contact input) (30 Hz max. with ON/OFF pulse width of 15 ms min.)
• No contact voltage pulse
<table>
<tr><th>Mode</th><th>Input frequency range</th><th>ON/OFF pulse width</th><th>ON voltage</th><th>OFF voltage</th><th>Input impedance</th></tr>
<tr><td>F1</td><td>0 to 30 kHz</td><td>16 μs min.</td><td>4.5 to 30 V</td><td>–30 to 2 V</td><td>10 kΩ</td></tr>
<tr><td>F2</td><td>0 to 25 kHz</td><td>20 μs min.</td><td></td><td></td><td></td></tr>
<tr><td>F3</td><td>0 to 50 kHz</td><td>9 μs min.</td><td></td><td></td><td></td></tr>
</table>
• Open collector
<table>
<tr><th>Mode</th><th>Input frequency range</th><th>ON/OFF pulse width</th></tr>
<tr><td>F1</td><td>0 to 30 kHz</td><td>16 μs min.</td></tr>
<tr><td>F2</td><td>0 to 25 kHz</td><td>20 μs min.</td></tr>
<tr><td>F3</td><td>0 to 50 kHz</td><td>9 μs min.</td></tr>
</table>
Note: The Up/Down Counting Pulse Meter will malfunction if a pulse greater than the input frequency range is input. SYSERR may appear on the display.</td></tr>
<tr><td colspan="2">Connectable sensors</td><td>ON residual voltage: 3 V max.
OFF leakage current: 1.5 mA max.
Load current: Must have a switching capacity of 20 mA or higher.
Must be able to properly switch load currents of 5 mA or less.</td></tr>
<tr><td colspan="2">Max. No. of display digits</td><td>5 (–19999 to 99999)</td></tr>
<tr><td colspan="2">Comparative output response time</td><td>1 ms max.: Transistor output; 10 ms max.: Relay contact output
(time until the comparative output is made when there is a forced sudden change in the input signal from 15% to 95% or 95% to 15%)</td></tr>
<tr><td colspan="2">Linear output response time</td><td>10 ms max. (time until the final analog output value is reached when there is a forced sudden change in the input signal from 15% to 95% or 95% to 15%)</td></tr>
<tr><td colspan="2">Insulation resistance</td><td>20 MΩ min. (at 500 VDC)</td></tr>
<tr><td colspan="2">Dielectric strength</td><td>2,300 VAC for 1 min between external terminals and case</td></tr>
<tr><td colspan="2">Noise immunity</td><td>100 to 240 VAC models:
±1,500 V at power supply terminals in normal or common mode
(waveform with 1-ns rising edge and pulse width of 1 μs/100 ns)
24 VAC/VDC models:
±1,500 V at power supply terminals in normal or common mode
(waveform with 1-ns rising edge and pulse width of 1 μs/100 ns)</td></tr>
<tr><td colspan="2">Vibration resistance</td><td>Frequency: 10 to 55 Hz; Acceleration: 50 m/s^2, 10 sweeps of 5 min each in X, Y, and Z directions</td></tr>
<tr><td colspan="2">Shock resistance</td><td>150 m/s^2 (100 m/s^2 for relay outputs) 3 times each in 3 axes, 6 directions</td></tr>
<tr><td colspan="2">Weight</td><td>Approx. 300 g (Base Unit only)</td></tr>
<tr><td rowspan="3">Degree of protection</td><td>Front panel</td><td>Conforms to NEMA 4X for indoor use (equivalent to IP66)</td></tr>
<tr><td>Rear case</td><td>IP20</td></tr>
<tr><td>Terminals</td><td>IP00 + finger protection (VDE0106/100)</td></tr>
<tr><td colspan="2">Memory protection</td><td>EEPROM (non-volatile memory)
Number of rewrites: 100,000</td></tr>
<tr><td colspan="2">Applicable standards</td><td>UL61010-1, CSA C22.2 No. 61010-1-04
EN61010-1 (IEC61010-1): Pollution degree 2/Overvoltage category II
EN61326-1</td></tr>
<tr><td colspan="2">EMC</td><td>EMI: EN61326 industrial applications
Electromagnetic radiation interference
CISPR 11 Group 1, Class A
Terminal interference voltage
CISPR 11 Group 1, Class A
EMS: EN61326 industrial applications
Electrostatic Discharge Immunity
EN61000-4-2: 4 kV (contact), 8 kV (in air)
Radiated Electromagnetic Field Immunity
EN61000-4-3: 10 V/m sine wave amplitude modulation (80 MHz to 1 GHz, 1.4 to 2 GHz)
Electrical Fast Transient/Burst Noise Immunity
EN61000-4-4: 2 kV (power line), 1 kV (I/O signal line)
Surge Immunity
EN61000-4-5: 1 kV with line (power line), 2 kV with ground (power line)
Conducted Disturbance Immunity
EN61000-4-6: 3 V (0.15 to 80 MHz)
Power Frequency Magnetic Immunity
EN61000-4-8: 30 A/m (50 Hz) continuous time
Voltage Dips and Interruptions Immunity
EN61000-4-11: 0.5 cycle, 0°/180°, 100% (rated voltage)</td></tr>
</table>







chanhvinh.com

Operation

■ Functions (Operating Modes)

F1 to F3

Function name	Function No.
Individual inputs	F1
Phase differential inputs	F2
Pulse counting input	F3

Function	Operation	Operation image (application)
F1 Individual inputs	Counts input A as incremental pulses and input B as decremental pulses. The count is incremented on the rising edge of input A and decremented on the rising edge of input B. If both inputs rise at the same time, the count is not changed. The count is incremented when input B is later than input A and decremented when input B is earlier than input A. 	Counting the number of people entering an area 
F2 Phase differential inputs	This function is normally used when connected to an incremental rotary encoder. The count is incremented on the falling edge of input B when input A is OFF. The count is decremented on the rising edge of input B when input A is OFF. 	Detecting position and speed on a semiconductor wafer conveyor line 
F3 Pulse counting input	Counted on the rising edge of input A 	Counting the number of workpieces 

Note: 1. Meaning of H and L in Display

Symbol	Input method	No-voltage input
H		Short-circuit
L		Open

2. Requires at least half the minimum signal width. If there is less than half, a ±1 count error may occur.

Input Type Setting

	NO: Voltage pulse high	NC: Voltage pulse low
No-contact or voltage pulse input	00	01
Contact	10	11

chanhvinh.com


■ What Is Prescaling?

Prescaling converts the count value to any numeric value.

To display □□□□.□ mm in a system that outputs 250 pulses for a 0.5-m feed,

the length per pulse = 500 mm (0.5 m) ÷ 250 = 2.

1. The prescale value for the K3HB-C is set using the mantissa X × exponent Y, so the prescale value = 2.0000 × 10°,
   X = 2.000, and Y = 00.
2. Next, set the decimal point position for one digit to the right of the decimal point: ▫▫▫▫.▫



chanhvinh.com

Common Specifications

■ Event Input Ratings

K3HB-P/-C	HOLD, RESET, BANK1, BANK2, BANK4	
Contact	ON: 1 kΩ max., OFF: 100 kΩ min.	
No-contact	ON residual voltage:	2 V max.
	OFF leakage current:	0.1 mA max.
	Load current:	4 mA max.
	Maximum applied voltage:	30 VDC max.

■ Output Ratings

Contact Output

Item	Resistive loads (250 VAC, cosϕ=1; 30 VDC, L/R=0 ms)	Inductive loads (250 VAC, closed circuit, cosϕ=0.4; 30 VDC, L/R=7 ms)
Rated load	5 A at 250 VAC 5 A at 30 VDC	1 A at 250 VAC 1 A at 30 VDC
Rated through current	5 A	
Mechanical life expectancy	5,000,000 operations	
Electrical life expectancy	100,000 operations	

Transistor Outputs

Maximum load voltage	24 VDC
Maximum load current	50 mA
Leakage current	100 μA max.

Linear Output

Item / Outputs	0 to 20 mA	4 to 20 mA	0 to 5 V	1 to 5 V	0 to 10 V
Allowable load impedance	500 Ω max.		5 kΩ min.		
Resolution	Approx. 10,000				
Output error	±0.5% FS		±0.5% FS (±0.15 V for 1 V or less and no output for 0 V)		

Serial Communications Output

Item / Type	RS-232C, RS-485
Communications method	Half duplex
Synchronization method	Start-stop synchronization (asynchronous)
Baud rate	9600/19200/38400 bps
Transmission code	ASCII
Data length	7 bits or 8 bits
Stop bit length	2 bits or 1 bit
Error detection	Vertical parity and FCS
Parity check	Odd, even

BCD Output I/O Ratings (Input Signal Logic: Negative)

I/O signal name		Item		Rating
Inputs	REQUEST CCOMPEN-SATION RESET	Input signal		No-voltage contact input
		Input current for no-voltage input		10 mA
		Signal level	ON voltage	1.5 V max.
			OFF voltage	3 V min.
Outputs	DATA POLARITY OVER DATA VALID RUN	Maximum load voltage		24 VDC
		Maximum load current		10 mA
		Leakage current		100 μA max.
	OUT1 OUT2 OUT3 OUT4 OUT5	Maximum load voltage		24 VDC
		Maximum load current		50 mA
		Leakage current		100 μA max.

Refer to the *K3HB Communications User's Manual* (Cat. No. N129) for details on serial and DeviceNet communications.

chanhvinh.com

DeviceNet Communications

<table>
<tr><td colspan="2">Communications protocol</td><td>Conforms to DeviceNet</td></tr>
<tr><td rowspan="3">Supported communications</td><td rowspan="2">Remote I/O communications</td><td>Master-Slave connection (polling, bit-strobe, COS, cyclic)
Conforms to DeviceNet communications standards.</td></tr>
<tr><td>I/O allocations</td><td>Allocate any I/O data using the Configurator.
Allocate any data, such as DeviceNet-specific parameters and variable area for Digital Indicators.
Input area: 2 blocks, 60 words max.
Output area: 1 block, 29 words max.
(The first word in the area is always allocated for the Output Execution Enabled Flags.)</td></tr>
<tr><td>Message communications</td><td>Explicit message communications
CompoWay/F communications commands can be executed
(using explicit message communications)</td></tr>
<tr><td colspan="2">Connection methods</td><td>Combination of multi-drop and T-branch connections (for trunk and drop lines)</td></tr>
<tr><td colspan="2">Baud rate</td><td>DeviceNet: 500, 250, or 125 Kbps (automatic follow-up)</td></tr>
<tr><td colspan="2">Communications media</td><td>Special 5-wire cable (2 signal lines, 2 power supply lines, 1 shield line)</td></tr>
<tr><td colspan="2">Communications distance</td><td>
<table>
<tr><th>Baud rate</th><th>Network length (max.)</th><th>Drop line length (max.)</th><th>Total drop line length (max.)</th></tr>
<tr><td>500 Kbps</td><td>100 m max.
(100 m max.)</td><td>6 m max.</td><td>39 m max.</td></tr>
<tr><td>250 Kbps</td><td>100 m max.
(250 m max.)</td><td>6 m max.</td><td>78 m max.</td></tr>
<tr><td>125 Kbps</td><td>100 m max.
(500 m max.)</td><td>6 m max.</td><td>156 m max.</td></tr>
</table>
The values in parentheses are for Thick Cable.
</td></tr>
<tr><td colspan="2">Communications power supply</td><td>24-VDC DeviceNet power supply</td></tr>
<tr><td colspan="2">Allowable voltage fluctuation range</td><td>11 to 25-VDC DeviceNet power supply</td></tr>
<tr><td colspan="2">Current consumption</td><td>50 mA max. (24 VDC)</td></tr>
<tr><td colspan="2">Maximum number of nodes</td><td>64 (DeviceNet Configurator is counted as one node when connected.)</td></tr>
<tr><td colspan="2">Maximum number of slaves</td><td>63</td></tr>
<tr><td colspan="2">Error control checks</td><td>CRC errors</td></tr>
<tr><td colspan="2">DeviceNet power supply</td><td>Supplied from DeviceNet communications connector</td></tr>
</table>


chanhvinh.com

Connections

■ External Connection Diagrams


Terminal Arrangements

Note: Refer to *Internal Block Diagram* on page 10 for information on isolation.



A Operating Power Supply


100 to 240 VAC
24 VAC/VDC



*Check the required power supply type.


B Sensor Power Supply/Output

Sensor power supply + PASS output




<CPA>

Sensor power supply + linear output




<L2A> <L1A>

Sensor power supply



<A>


Sensor power supply + communications




RS-485 <FLK3A>
RS-232C <FLK1A>

C Relays, Transistors, BCD and DeviceNet


Relay Outputs <C1>




Relay Outputs <C2>



Transistor Outputs <T1> <T2>




DeviceNet Connector (Included) <DRT>



1: V– (Power supply cable: Black)
2: CAN L (Communications cable: Blue)
3: Shield
4: CAN H (Communications cable: White)
5: V+ (Power supply cable: Red)
Applicable Connector:
HR31-5.08P-5SC (01)
(HIROSE ELECTRIC CO., LTD.)
* Attach the provided crimp terminals.


BCD (NPN Open Collector): <BCD>
Applicable Connector (Sold separately)
HDR-E50MAG1
(HONDA TSUSHIN KOGYO CO., LTD.)
Special Cable (Sold separately)
K32-BCD (OMRON)
(HDR-E50MAG1 with 0.3-m cable)




The BCD COMMON is shared.
The pins indicated in the above diagram as blank (white) boxes have been removed.

*Only one of the following can be used for each Digital Indicator: communications, BCD, or DeviceNet.

Contact Outputs



Transistor Outputs (NPN Open Collector)




Safety Standards Conformance

- Always use a EN/IEC-compliant power supply with reinforced insulation or double insulation for the DeviceNet power supply.
- The product must be used indoors for the above applicable standards to apply.


chanhvinh.com

E Pulse Inputs




NPN Input Model

• NPN input section



Connectable Sensors	ON residual voltage: 3 V OFF leakage current: 1.5 mA max.


• Voltage pulse input section



Connectable Sensors	ON voltage: 4.5 to 30 V OFF voltage: -30 to 2 V


Note: A 2-wire DC sensor can also be connected. Check the ratings and characteristics tables, however, for the connection conditions.

D Event Inputs





Note: The actual terminal label abbreviates "COMPENSATION" to "CMP."

- Use terminal pin D6 as the common terminal.
- Use NPN open collector or no-voltage contacts for event input.
  PNP types are also available.




BCD Output Cable

Model	Shape	Pin arrangement
K32-BCD	 Cover: HDR-E50LPA5 (manufactured by Honda Tsushin Co., Ltd.) Connector: HDR-E50MAG1 (manufactured by Honda Tsushin Co., Ltd.) D-sub connector (37-pin female) Cover: 17JE-37H-1A (manufactured by DDK) Connector: Equivalent to 17JE-13370-02 (manufactured by DDK) Stud: 17L-002A (manufactured by DDK)	

Note: The BCD Output Cable has a D-sub plug. Cover: 17JE-37H-1A (manufactured by DDK); Connector: equivalent to 17JE-23370-02 (D1) (manufactured by DDK)


Special Cable (for Event Inputs with 8-pin Connector)

Model	Appearance	Wiring
K32-DICN		▶ 1 N/C 2 S-TMR 3 HOLD 4 RESET 5 N/C 6 COM 7 BANK4 8 BANK2 9 BANK1 10 COM

chanhvinh.com

■ Derating Curve for Sensor Power Supply (Reference Values)


For 12V



Note: 1. The above values were obtained under test conditions with the standard mounting. The derating curve will vary with the mounting conditions, so be sure to adjust accordingly.

2. Internal components may be deteriorated or damaged. Do not use the Digital Indicator outside of the derating range (i.e., do not use it in the area labeled ①, above).

■ Internal Block Diagram




chanhvinh.com

■ BCD Output Timing Chart


A REQUEST signal from a Programmable Controller or other external device is required to read BCD data.

Single Sampling Data Output



The data is set in approximately 30 ms from the rising edge of the REQUEST signal and the DATA VALID signal is output.
When reading the data from a Programmable Controller, start reading the data when the DATA VALID signal turns ON.
The DATA VALID signal will turn OFF 40 ms later, and the data will turn OFF 16 ms after that.


Continuous Data Output




Measurement data is output every 64 ms while the REQUEST signal remains ON.

Note: If HOLD is executed when switching between data 1 and data 2, either data 1 or data 2 is output depending on the timing of the hold signal. The data will not go LOW.


• The K3HB BCD output model has an open collector output, so wired OR connection is possible






Note: Leave 20 ms min. between DATA VALID turning OFF and the REQUEST signal.

Programmable Controller Connection Example



Display Unit Connection Example



<M7E Digital Display Unit>

Note: The BCD output connector pin number is the D-sub connector pin number when the BCD Output Cable (sold separately) is connected. This number differs from the pin number for the Digital Indicator narrow pitch connector (manufactured by Honda Tsushin Kogyo Co., Ltd.).

Refer to the following User's Manual for application precautions and other information required when using the Digital Indicator:
K3HB-R/P/C Digital Indicator User's Manual (Cat. No. N136)
The manual can be downloaded from the following site in PDF format: OMRON Industrial Web http://www.fa.omron.co.jp

chanhvinh.com

■ Component Names and Functions

Max./Min. status indicator

Turns ON when the maximum value or minimum value is displayed in the RUN level.

Level/bank display

In RUN level, displays the bank if the bank function is ON. (Turns OFF if the bank function is OFF.)
In other levels, displays the current level.

Comparative output status indicators

Display the status of comparative outputs.

Status indicators

Display	Function
CMW	Lit when communications writing is ON (enabled) and not lit when OFF (prohibited).
Hold	Turns ON/OFF when hold input turns ON/OFF.

PV display

Displays PVs, maximum values, minimum values, parameter names, and error names.

Position meter


Displays the position of the PV with respect to a desired scale.


SV display

Displays SV and monitor values.

SV display status indicators

Indicator	Function
T	Turns ON when parameters for which teaching can be performed are displayed.
5, 4, 3, 2, 1	In RUN level, turn ON when the comparative set value 1, 2, 3, 4, or 5 is displayed.





MAX/MIN Key

Used to switch the display between the PV, maximum value, and minimum value and to reset the maximum and minimum values.

LEVEL Key

Used to switch level.

MODE Key

Used to switch the parameters displayed.

SHIFT Key

Used to change parameter settings. When changing a set value, this key is used to move along the digits.


UP Key

When changing a set value, this key is used to change the actual value.


chanhvinh.com

■ Dimensions






Character Size for Main Display (mm)



Panel Cutout Dimensions



*2. Leave a distance of at least 140 mm when using the Wate Cover Y92A-49N.

Note: Mounting Recommended Panel Thickness 1 to 8 mm.
Mount the product horizontally.

*1. DeviceNet models: 97 mm


Terminal: M3, Terminal Cover: Accessory

Wiring Precautions

- For terminal blocks, use the crimp terminals suitable for M3 screws.
- Tighten the terminal screws to the recommended tightening torque of approx. 0.5 N·m.
- To prevent inductive noise, separate the wiring for signal lines from that for power lines.


Wiring

- Use the crimp terminals suitable for M3 screws shown below.



Unit Stickers (included)


- No unit stickers are attached to the Digital Indicator.
- Select the appropriate units from the unit sticker sheets provided.




Note: For measurements for commercial purposes, be sure to use the unit required by any applicable laws or regulations.

Mounting Method

1. Insert the K3HB into the mounting cutout in the panel.
2. Insert watertight packing around the Unit to make the mounting watertight.




3. Insert the adapter into the grooves on the left and right sides of the rear case and push until it reaches the panel and is fixed in place.




LCD Field of Vision

The K3HB is designed to have the best visibility at the angles shown in the following diagram.




Watertight Cover

Y92A-49N



Rubber Packing

K32-P1



If the rubber packing is lost or damaged, it can be ordered using the following model number: K32-P1.

(Depending on the operating environment, deterioration, contraction, or hardening of the rubber packing may occur and so, in order to ensure the level of waterproofing specified in NEMA4, periodic replacement is recommended.)

Note: Rubber packing is provided with the Controller.

chanhvinh.com

Main Functions

■ Main Functions and Features

Measurement

Function FUnC

The K3HB-R has the following six functions for receiving and displaying input pulses.

F1: Rotation (rpm)/circumferential speed

F2: Absolute ratio

F3: Error ratio

F4: Rotational difference

F5: Flow rate ratio

F6: Passing time

The K3HB-P has the following six functions for receiving and displaying input pulses.

F1: Passing speed

F2: Cycle

F3: Time difference

F4: Time band

F5: Measuring length

F6: Interval

The K3HB-C has the following three functions for receiving and displaying input pulses.

F1: Individual inputs

F2: Phase differential inputs

F3: Pulse counting input

Filters

Input Types in-tA, in-tb, in-tA

Specify the types of sensor connected to input A and input B.

Compensation

Compensation CoMPn, CoM-P

The display can be changed to a preset compensation value using the compensation input.

Key Operations

Teaching

The present measurement value can be used as a scaling value.

Key Protection

Key protection restricts level or parameter changes using the keys to prevent unintentional key operations and malfunctions.

Outputs

Comparative Output Pattern oUt-P

Zone and level comparative output patterns can be selected for comparative outputs.

Output OFF Delay oFF-d

Delays turning OFF comparatives for a set period. This can be used to provide sufficient time to read the comparative output ON status when the comparative result changes at short intervals.

Shot Output SHot

Turns ON the comparative output for a specific time.

Output Logic oUt-n

Reverses the output logic of comparative results.

Output Test tESt

Output operation can be checked without using actual input signals by using the keys to set a test measurement value.

Linear Outputs LSEtC, LSEtA, LSEtH, LSEtL

A current or voltage proportional to the change in the measurement value can be output.

Standby Sequence StdbY

The comparison outputs can be kept OFF until the measurement value enters the PASS range.

chanhvinh.com

Display

Display Value Selection dISP

The display value can be set to the present value, the maximum value, or the minimum value.

Display Color Selection COLOR

The present value display color can be set to green or red. The color of the present value can also be switched according to the comparative output.

Display Refresh Period dREF

When the input changes rapidly, the display refresh period can be lengthened to control flickering and make the display easier to read.

Position Meter POS-T, POS-H, POS-L

The present measurement value can be displayed as a position in relation to the scaling width on a 20-gradation position meter.

Prescale PS.AU, PS.AY, PS.bU, PS.bY

The input signal can be converted and displayed as any value.

Comparative Set Value Display Su.dSP

Select whether or not to display the comparative value during operation.

Display auto-return rEt

Automatically returns the display to RUN level when there are no key operations (e.g., max./min. switching, bank settings using keys).

Other

Bank Selection bnK-C

Switch between 8 comparative value banks using the keys on the front panel or external inputs. A set of set comparative values can be selected as a group.

Bank Copy COPY

Any bank settings can be copied to all banks.

Interruption Memory MEMO

The measured value can be recorded when the power supply is interrupted.

ALL DIMENSIONS SHOWN ARE IN MILLIMETERS.
To convert millimeters into inches, multiply by 0.03937. To convert grams into ounces, multiply by 0.03527.

In the interest of product improvement, specifications are subject to change without notice.

chanhvinh.com

Terms and Conditions Agreement

Read and understand this catalog.
Please read and understand this catalog before purchasing the products. Please consult your OMRON representative if you have any questions or comments.

Warranties.
(a) Exclusive Warranty. Omron's exclusive warranty is that the Products will be free from defects in materials and workmanship for a period of twelve months from the date of sale by Omron (or such other period expressed in writing by Omron). Omron disclaims all other warranties, express or implied.
(b) Limitations. OMRON MAKES NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, ABOUT NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE OF THE PRODUCTS. BUYER ACKNOWLEDGES THAT IT ALONE HAS DETERMINED THAT THE
PRODUCTS WILL SUITABLY MEET THE REQUIREMENTS OF THEIR INTENDED USE.
Omron further disclaims all warranties and responsibility of any type for claims or expenses based on infringement by the Products or otherwise of any intellectual property right. (c) Buyer Remedy. Omron's sole obligation hereunder shall be, at Omron's election, to (i) replace (in the form originally shipped with Buyer responsible for labor charges for removal or replacement thereof) the non-complying Product, (ii) repair the non-complying Product, or (iii) repay or credit Buyer an amount equal to the purchase price of the non-complying Product; provided that in no event shall Omron be responsible for warranty, repair, indemnity or any other claims or expenses regarding the Products unless Omron's analysis confirms that the Products were properly handled, stored, installed and maintained and not subject to contamination, abuse, misuse or inappropriate modification. Return of any Products by Buyer must be approved in writing by Omron before shipment. Omron Companies shall not be liable for the suitability or unsuitability or the results from the use of Products in combination with any electrical or electronic components, circuits, system assemblies or any other materials or substances or environments. Any advice, recommendations or information given orally or in writing, are not to be construed as an amendment or addition to the above warranty.
See http://www.omron.com/global/ or contact your Omron representative for published information.

Limitation on Liability; Etc.
OMRON COMPANIES SHALL NOT BE LIABLE FOR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, LOSS OF PROFITS OR PRODUCTION OR COMMERCIAL LOSS IN ANY WAY CONNECTED WITH THE PRODUCTS, WHETHER SUCH CLAIM IS BASED IN CONTRACT, WARRANTY, NEGLIGENCE OR STRICT LIABILITY.
Further, in no event shall liability of Omron Companies exceed the individual price of the Product on which liability is asserted.

Suitability of Use.
Omron Companies shall not be responsible for conformity with any standards, codes or regulations which apply to the combination of the Product in the Buyer's application or use of the Product. At Buyer's request, Omron will provide applicable third party certification documents identifying ratings and limitations of use which apply to the Product. This information by itself is not sufficient for a complete determination of the suitability of the Product in combination with the end product, machine, system, or other application or use. Buyer shall be solely responsible for determining appropriateness of the particular Product with respect to Buyer's application, product or system. Buyer shall take application responsibility in all cases.
NEVER USE THE PRODUCT FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY OR IN LARGE QUANTITIES WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISKS, AND THAT THE OMRON PRODUCT(S) IS PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

Programmable Products.
Omron Companies shall not be responsible for the user's programming of a programmable Product, or any consequence thereof.

Performance Data.
Data presented in Omron Company websites, catalogs and other materials is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of Omron's test conditions, and the user must correlate it to actual application requirements. Actual performance is subject to the Omron's Warranty and Limitations of Liability.

Change in Specifications.
Product specifications and accessories may be changed at any time based on improvements and other reasons. It is our practice to change part numbers when published ratings or features are changed, or when significant construction changes are made. However, some specifications of the Product may be changed without any notice. When in doubt, special part numbers may be assigned to fix or establish key specifications for your application. Please consult with your Omron's representative at any time to confirm actual specifications of purchased Product.

Errors and Omissions.
Information presented by Omron Companies has been checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical or proofreading errors or omissions.

2014.9

In the interest of product improvement, specifications are subject to change without notice.

OMRON Corporation
Industrial Automation Company

http://www.ia.omron.com/

(c)Copyright OMRON Corporation 2014 All Right Reserved.

chanhvinh.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Omron:

K3HB-CNB 24VAC/VDC K3HB-CNB 100-240VAC

chanhvinh.com